



- NOTES :**
1. ALL MOUNTING HOLES TO BE 4 mm DIA.
  2. SECURE RAIL AND RESIDUAL CURRENT CIRCUIT BREAKER/S WITH SELF-TAPPING SCREWS (COUNTERSUNK FOR RAILS).
  3. MOUNTING BRACKET TO BE RIVETED TO BASE PLATE.
  4. WHEN USED WITH DOUBLE OUTREACH COLUMNS, USE AN ADDITIONAL BREAKER IN POSITION SHOWN.

ITEM No.	QTY.	DESCRIPTION
1	1	ALUMINIUM BASE PLATE 560mm X 85mm X 3mm
2	1	STAINLESS STEEL 5 mm "STANKO" LUG
3	1	STAINLESS STEEL 5 mm WASHER
4	1	STAINLESS STEEL 5 mm SPLIT WASHER
5	1	STAINLESS STEEL 5 mm BOLT
6	2	STAINLESS STEEL 5 mm NUTS
7	AR	RCD/MCB - 10kA - 10 A DIN
8	2	ACTIVE AND NEUTRAL LINKS (1 EACH)
9	1	MOUNTING BRACKET
10	AR	CABLE Cu 4 sqmm PVC RED SDI
11	1	DIN RAIL FOR RCD/MCBs
12	1	SERIES SURGE PROTECTOR 15kA
13	1	DIN RAIL FOR SURGE PROTECTION DEVICE

TO BE READ IN CONJUNCTION WITH DRAWING SS5012  
 ABBREVIATION: AR = AS REQUIRED

SWITCH PACK LIGHTING COLUMN WITH SURGE PROTECTOR

SCALE: N.T.S.

0 ISSUED AS A STANDARD DRAWING				AUG 2020	CJ	AF	DRAWN CJ	CHECKED PB	SUBDIVISION DEVELOPMENT GUIDELINES STANDARD DRAWINGS LIGHTING			
No.	DESCRIPTION	DATE	INIT.	DEPT/COMPANY.	DESIGNED CJ	CHECKED PB	DATE AUGUST 2020	DATE AUGUST 2020	LED LUMINARE SWITCH PACK DETAILS TYPICAL DETAILS			
AMENDMENTS							DATE AUGUST 2020	DATE AUGUST 2020	NTG PROJECT No. - NTG ASSET No. - SHEET No. 14 OF 16 NTG DRAWING No. SS5013 AMENDMENT 0 SHEET SIZE A1			

